



## SYSTEM COMPONENTS:

### LOW FREQUENCY DRIVER:

Cone Kit:	123A-1
Nom. Impedance:	C8R2212
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	6
D.C. Resistance Ohms:	20-1200
	4.5 minimum
	5.5 maximum
Gap Gauge:	.044"
Notes:	Aquaplas
If Not Serviceable,	2213H
Replace With:	(Reverse Polarity)
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No.
	Slightly different. Replace both units
	in a stereo pair.
Additional Parts Currently Available*:	
Dome:	31385
Trim Gasket:	32756

### MID RANGE DRIVER:

Cone Kit:	LE5-2
Nom. Impedance:	C8RLE52
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	4
D.C. Resistance Ohms:	75-3000
	5.5 minimum
	6.5 maximum
Gap Gauge:	.040"
Notes:	Dome Inverted
If Not Serviceable,	
Replace With:	LE5-10
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No.
	Slightly different. Replace both units
	in a stereo pair.

### MID RANGE DRIVER (Cont'd)

#### Additional Parts Currently Available\*:

Dome:	54721
Trim Gasket:	29931

### HIGH FREQUENCY DRIVER:

Diaphragm Kit:	LE25
Nom. Impedance:	D8RLE25
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	3
D.C. Resistance Ohms:	500-1200
	3.7 minimum
	4.2 maximum
Gap Gauge:	.029"
Notes:	
If Not Serviceable,	
Replace With:	035TiA
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No.
	Slightly different. Replace both units
	in a stereo pair.

#### Additional Parts Currently Available\*:

Trim Ring:	50402
Mounting Gasket:	50949-01
Dome:	21606

## SYSTEM SPECIFICATIONS:

Nominal Impedance:	8 Ohm
Power Capacity:	50 Watts
	Continuous Program
Crossover Frequencies:	1500 Hz, 6000 Hz
Sensitivity:	78dB (1 Watt @ 15 Feet)
Enclosure Dim:	14-1/4" x 23-1/2" x 13-5/8" D
	36.2cm x 59.7cm x 34.6cm
Shipping Weight:	55 lbs. - 25 kg.
Additional Parts Currently Available*:	
Grill:	G100-Cloth
Binding Posts: Red:	56131
Black:	56130

\*Other parts may also be available. Check with JBL for details.