



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

Cone Kit: LE111H
 Nom. Impedance: C8RLE111H
 Dynamic Test Input V: 8 Ohm
 Sweep Frequency Hz: 6
 D.C. Resistance Ohms: 20-1200
 Gap Gauge: 4.3 min/5.2 max
 Notes: .053"
 Aquaplas On Back
 Of Cone

If Not Serviceable, Replace With: LE10H-1

Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

Additional Parts Currently Available*:

Dome: 31385
 Mounting Gasket: 21770
 Trim Gasket: 21813

MID RANGE DRIVER:

Cone Kit: LE5-10
 Nom. Impedance: C8RLE510
 Dynamic Test Input V: 8 Ohm
 Sweep Frequency Hz: 4
 D.C. Resistance Ohms: 75-3000
 Gap Gauge: 4.9 min/6.1 max
 Notes: .040"

If Not Serviceable, Replace With: Currently Available
 or LE5-12

Visual Change: Yes
 Baffle Modification: No
 Exact Acoustic Replacement: Yes

MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available*:

Dome: 51686
 Mounting Gasket: 21771
 Trim Gasket: 29931

HIGH FREQUENCY DRIVER:

Diaphragm Kit: 033
 Nom. Impedance: D8R033
 Dynamic Test Input V: 8 Ohm
 Sweep Frequency Hz: 5
 D.C. Resistance Ohms: 200-1200
 Gap Gauge: 3.6 min/4.4 max
 Notes: .031"
 Test With Network

If Not Serviceable, Replace With: No replacement available.

034 not safe for L110A System.

Visual Change: N/A
 Baffle Modification: N/A
 Exact Acoustic Replacement: N/A

Additional Parts Currently Available*:

Mounting Gasket: 57754

SYSTEM SPECIFICATIONS:

Nom. Impedance: 8 Ohm
 Max Rec. Amp Power: 250 Watts Per Channel
 Crossover Frequencies: 1000 Hz, 4000 Hz
 Sensitivity: 89dB (1 Watt @ 1 Meter)
 Enclosure Dim: 23-1/2" x 14-1/4" x 11-1/4" D
 597mm x 362mm x 286mm
 Shipping Weight: 53 lbs. - 24 kg.
 Additional Parts Currently Available*:
 Binding Posts: Red: 56131
 Black: 56130

*Other parts may also be available. Check with JBL for details.