



## SYSTEM COMPONENTS:

### LOW FREQUENCY DRIVER:

Cone Kit:	122A (L166)
Nom. Impedance:	122A-1 (L166-A)
Dynamic Test Input V:	C8R129H
Sweep Frequency Hz:	8 Ohm
D.C. Resistance Ohms:	6
Gap Gauge:	20-1200
Notes:	4.5 min/5.5 max
	.053"
	Mass Ring. Cone Kit
	may have aquaplas on cone instead of mass ring.
If Not Serviceable, Replace With:	128H-1
Visual Change:	Yes
Baffle Modification:	No
Exact Acoustic Replacement:	No. Use as last resort.
	Replace both units in a stereo pair.
Additional Parts Currently Available*:	
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806

### MID RANGE DRIVER:

Cone Kit:	LE5-8
Nom. Impedance:	C8RLE510
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	4
D.C. Resistance Ohms:	75-3000
Gap Gauge:	5.6 min/6.8 max
Notes:	.040"
	No
If Not Serviceable, Replace With:	LE5-12
Visual Change:	No

### MID RANGE DRIVER (Cont'd)

Baffle Modification:	No
Exact Acoustic Replacement:	Yes
Additional Parts Currently Available*:	
Dome:	51868
Trim Gasket:	29931

### HIGH FREQUENCY DRIVER:

Diaphragm Kit:	066
Nom. Impedance:	D8R066
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	5
D.C. Resistance Ohms:	200-1200
Gap Gauge:	3.5 min/4.4 max
Notes:	.031"
	Test With Network
If Not Serviceable, Replace With:	Currently Available.
Can Also Be Replaced With:	044.
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No. Slightly different.
	Replace both units in a stereo pair.

## SYSTEM SPECIFICATIONS:

Nom. Impedance:	8 Ohm
Power Capacity:	75 Watts Continuous
	Program
Crossover Frequencies:	1000 Hz, 6000 Hz
Sensitivity:	76dB (1 Watt @ 15 Feet)
Enclosure Dim:	14-1/4" x 23-1/2" x 13" D
	36.2cm x 59.7cm x 33cm
Shipping Weight:	55 lbs. - 25 kg.

\*Other parts may also be available. Check with JBL for details.