



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

117H-1
Cone Kit: C8R117
Nom. Impedance: 8 Ohm
Dynamic Test Input V: 5
Sweep Frequency Hz: 30-1200
D.C. Resistance Ohms: 5.0 minimum
6.0 maximum

Gap Gauge: .051"
Notes: Aquaplas On Cone

If Not Serviceable,
Replace With: 116H-3
Visual Change: Yes
Baffle Modification: No
Exact Acoustic Replacement: No. Slightly
different. Replace both units in a stereo pair.

Additional Parts Currently Available*:

Dome: 62112
Mounting Gasket: 52671
Trim Gasket: 52316

MID RANGE DRIVER:

LE5-12
Cone Kit: C8RLE510
Nom. Impedance: 8 Ohm
Dynamic Test Input V: 4
Sweep Frequency Hz: 75-3000
D.C. Resistance Ohms: 4.9 minimum
6.1 maximum

Gap Gauge: .040"
Notes:
If Not Serviceable,
Replace With: Currently Available

Visual Change: N/A
Baffle Modification: N/A
Exact Acoustic Replacement: N/A

Additional Parts Currently Available*:

MID RANGE DRIVER (Cont'd)

Dome: 51686
Mounting Gasket: 21771
Trim Gasket: 29931
Terminal Board: 53225

HIGH FREQUENCY DRIVER:

034
Diaphragm Kit: D8R034
Nom. Impedance: 8 Ohm
Dynamic Test Input V: 2.5
Sweep Frequency Hz: 200-2000
D.C. Resistance Ohms: 5.4 minimum
6.6 maximum

Gap Gauge: .031"
Notes: Test With Network

If Not Serviceable,
Replace With: Currently Available

Visual Change: N/A
Baffle Modification: N/A
Exact Acoustic Replacement: N/A

Additional Parts Currently Available*:

Mounting Gasket: 57754
Screen: 60424
Screen Gasket: 60752

SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm
Max Recommended
Amp Power: 200 Watts Per Channel
Crossover Frequencies: 800 Hz, 3700 Hz
Sensitivity: 88dB (1 Watt @ 1 Meter)
Enclosure Dim: 21-3/8" x 13" x 10" D
543mm x 330mm x 254mm
Shipping Weight: 35 lbs. - 16 kg.
Additional Parts Currently Available*:
Binding Posts: Red: 56131
Black: 56130

*Other parts may also be available. Check with JBL for details.

JBL Consumer Products, Inc., 80 Crossways Park West, Woodbury, New York 11797

4/94 REV B