



SYSTEM COMPONENTS:

LOW FREQUENCY DRIVER:

Cone Kit:	128H
Nom. Impedance:	C8R128H
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	6
D.C. Resistance Ohms:	20-1200
Gap Gauge:	5.1 min/6.3 max
Notes:	.057"
If Not Serviceable, Replace With:	Aquaplas
Visual Change:	128H-1
Baffle Modification:	Yes
Exact Acoustic Replacement:	No
Additional Parts Currently Available*:	Yes
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806

MID RANGE DRIVER:

Cone Kit:	LE5-12
Nom. Impedance:	C8RLE510
Dynamic Test Input V:	8 Ohm
Sweep Frequency Hz:	4
D.C. Resistance Ohms:	75-3000
Gap Gauge:	4.9 min/6.1 max
Notes:	.040"
If Not Serviceable, Replace With:	Currently Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	51686
Terminal Board:	53225
Mounting Gasket:	21771
Trim Gasket:	29931

HIGH FREQUENCY DRIVER:

Diaphragm Kit:	044
Nom. Impedance:	D8R044
Dynamic Test Input V:	8 Ohm
	2

HIGH FREQUENCY DRIVER (Cont'd)

Sweep Frequency Hz:	2000-12000
D.C. Resistance Ohms:	5.4 min/6.6 max
Gap Gauge:	.032"
Notes:	Test With Network
If Not Serviceable, Replace With:	Currently Available
Can Also Be Replaced With:	034
Visual Change:	Yes
Baffle Modification:	Yes
Exact Acoustic Replacement:	No. Use as last resort.
Replace both units in a stereo pair.	
Additional Parts Currently Available*:	
Mounting Gasket:	62511
Screen:	60424

PASSIVE RADIATOR:

Cone Kit:	PR300
Notes:	CRPR300
If Not Serviceable, Replace With:	No Replacement Available
Visual Change:	N/A
Baffle Modification:	N/A
Exact Acoustic Replacement:	N/A
Additional Parts Currently Available*:	
Dome:	31385
Mounting Gasket:	20253
Trim Gasket:	52806

SYSTEM SPECIFICATIONS:

Nom. Impedance:	8 Ohm
Max Rec. Amp Power:	300 Watts Per Channel
Crossover Frequencies:	1100 Hz, 3700 Hz
Sensitivity:	89dB (1 Watt @ 1 Meter)
Enclosure Dim:	41-1/2" x 17" x 13" D
	1054mm x 432mm x 330mm
Shipping Weight:	80 lbs. - 36.4 kg.
Additional Parts Currently Available*:	
Grill:	G150BR
Binding Posts:	Red: 56131
	Black: 56130

*Other parts may also be available. Check with JBL for details.