


# L100A Century (Late Model)

**JBL**



## SYSTEM COMPONENTS:

**LOW FREQUENCY DRIVER:** 123A-3  
 Cone Kit: C8R2213  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 6  
 Sweep Frequency Hz: 20-1200  
 D.C. Resistance Ohms: 4.5 minimum  
 5.5 maximum  
 Gap Gauge: .048"  
 Notes: Aquaplas  
 If Not Serviceable,  
 Replace With: 2213H  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No.  
 Slightly different. Replace both units  
 in a stereo pair.  
 Additional Parts Currently Available\*:  
 Dome: 31385  
 Trim Gasket: 32756

**MID RANGE DRIVER:** LE5-2  
 Cone Kit: C8RLE52  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 4  
 Sweep Frequency Hz: 75-3000  
 D.C. Resistance Ohms: 5.5 minimum  
 6.5 maximum  
 Gap Gauge: .040"  
 Notes: Dome Inverted  
 If Not Serviceable,  
 Replace With: LE5-10  
 Visual Change: Yes  
 Baffle Modification: No  
 Exact Acoustic Replacement: No.  
 Slightly different. Replace both units  
 in a stereo pair.

## MID RANGE DRIVER (Cont'd)

Additional Parts Currently Available\*:  
 Dome: 54721  
 Trim Gasket: 29931

**HIGH FREQUENCY DRIVER:** LE25  
 Diaphragm Kit: D8RLE25  
 Nom. Impedance: 8 Ohm  
 Dynamic Test Input V: 3  
 Sweep Frequency Hz: 500-1200  
 D.C. Resistance Ohms: 3.7 minimum  
 4.2 maximum  
 Gap Gauge: .029"  
 Notes:  
 If Not Serviceable,  
 Replace With: 035TiA  
 Visual Change: Yes  
 Baffle Modification: Yes  
 Exact Acoustic Replacement: No.  
 Slightly different. Replace both units  
 in a stereo pair.  
 Additional Parts Currently Available\*:  
 Trim Ring: 50402  
 Mounting Gasket: 50949-01  
 Dome: 21606

## SYSTEM SPECIFICATIONS:

Nominal Impedance: 8 Ohm  
 Power Capacity: 50 Watts  
 Continuous Program  
 Crossover Frequencies: 1500 Hz, 6000 Hz  
 Sensitivity: 78dB (1 Watt @ 15 Feet)  
 Enclosure Dim: 14-1/4" x 23-1/2" x 13-5/8" D  
 36.2cm x 59.7cm x 34.6cm  
 Shipping Weight: 55 lbs. - 25 kg.  
 Additional Parts Currently Available\*:  
 Grill: G100-Cloth  
 Binding Posts: Red: 56131  
 Black: 56130

\*Other parts may also be available. Check with JBL for details.